

SLine110

Mode		FR (fullrange)		XO (crossover)
Crossover High-Pass (Lo-Cut)	Frequency	55 Hz		90 Hz
	Slope	18 dB/oct		18 dB/oct
	Shape	Bessel		Bessel
Crossover Low-Pass (Hi-Cut)	Frequency	20.000 Hz		20.000 Hz
	Slope	12 dB/oct		12 dB/oct
	Shape	Butterworth		Butterworth
PEQ1	Frequency	80 Hz		80 Hz
	Gain	7,8 dB		7,8 dB
	Q	3		3
	= Bandwidth	0,45 oct		0,45 oct
PEQ2	Frequency	364 Hz		364 Hz
	Gain	-6,7 dB		-6,7 dB
	Q	5		5
	= Bandwidth	0,27 oct		0,27 oct
PEQ3	Frequency	2810 Hz		2810 Hz
	Gain	-6,7 dB		-6,7 dB
	Q	5,5		5,5
	= Bandwidth	0,26 oct		0,26 oct
PEQ4	Frequency	4838 Hz		4838 Hz
	Gain	-10 dB		-10 dB
	Q	5		5
	= Bandwidth	0,28 oct		0,28 oct
PEQ5 Hi--Shf	Frequency	7746 Hz		7746 Hz
	Slope	6 dB/oct		6 dB/oct
	Gain	+5,7 dB		+5,7 dB
Limiter	Z(nom)	8 Ohm		8 Ohm
	P(rms)	250 Watt		250 Watt
	U(rms)	44,7 Volt		44,7 Volt