

SLine206

Mode		FR (fullrange)		XO (crossover)
Crossover High-Pass (Lo-Cut)	Frequency	80 Hz		90 Hz
	Slope	18 dB/oct		18 dB/oct
	Shape	Bessel		Bessel
Crossover Low-Pass (Hi-Cut)	Frequency	20.000 Hz		20.000 Hz
	Slope	12 dB/oct		12 dB/oct
	Shape	Butterworth		Butterworth
PEQ1	Frequency	180 Hz		180 Hz
	Gain	-7,3 dB		-7,3 dB
	Q	7		7
	= Bandwidth	0,21 oct		0,21 oct
PEQ2	Frequency	346 Hz		346 Hz
	Gain	-2,8 dB		-2,8 dB
	Q	3		3
	= Bandwidth	0,53 oct		0,53 oct
PEQ3	Frequency	2914 Hz		2914 Hz
	Gain	-7,6 dB		-7,6 dB
	Q	6,5		6,5
	= Bandwidth	0,22 oct		0,22 oct
PEQ4	Frequency	4803 Hz		4803 Hz
	Gain	-5,8 dB		-5,8 dB
	Q	9		9
	= Bandwidth	0,16 oct		0,16 oct
PEQ5	Frequency	13333 Hz		13333 Hz
	Gain	4,8 dB		4,8 dB
	Q	5		5
	= Bandwidth	0,28 oct		0,28 oct
Limiter	Z(nom)	8 Ohm		8 Ohm
	P(rms)	240 Watt		240 Watt
	U(rms)	44 Volt		44 Volt