

SLine208

Mode		FR (fullrange)		XO (crossover)
Crossover High-Pass (Lo-Cut)	Frequency	75 Hz		90 Hz
	Slope	18 dB/oct		18 dB/oct
	Shape	Bessel		Bessel
Crossover Low-Pass (Hi-Cut)	Frequency	20.000 Hz		20.000 Hz
	Slope	12 dB/oct		12 dB/oct
	Shape	Butterworth		Butterworth
PEQ1	Frequency	252 Hz		252 Hz
	Gain	-5 dB		-5 dB
	Q	3		3
	= Bandwidth	0,45 oct		0,45 oct
PEQ2	Frequency	694 Hz		694 Hz
	Gain	-3,7 dB		-3,7 dB
	Q	1,8		1,8
	= Bandwidth	0,76 oct		0,76 oct
PEQ3	Frequency	2872 Hz		2872 Hz
	Gain	-11 dB		-11 dB
	Q	5,5		5,5
	= Bandwidth	0,26 oct		0,26 oct
PEQ4	Frequency	5277 Hz		5277 Hz
	Gain	-9 dB		-9 dB
	Q	8		8
	= Bandwidth	0,18 oct		0,18 oct
PEQ5	Frequency	9625 Hz		9625 Hz
	Gain	5 dB		5 dB
	Q	7		7
	= Bandwidth	0,20 oct		0,20 oct
Limiter	Z(nom)	8 Ohm		8 Ohm
	P(rms)	300 Watt		300 Watt
	U(rms)	49 Volt		49 Volt